

Data Sheet

TOUCH-LESS SWITCH

SMART-PROX



1 - DESCRIPTION

i Unlike traditional push-buttons, the **manusa** SMART-PROX touch-less switch activates the door with no need of physical contact. The detection range is adjustable from 5 to 35 cm, depending on the site requirements. A light indicator confirms when the device is detecting, improving the experience of the end user.

It perfectly integrates in the environment thanks to its nice and modern design, very similar to the SMART selector, which can be mounted side-by-side. The device can be easily installed surface mounted, and the connection to the operator is done using the Manusa BUS (for Visio operator), or through a dry contact (for other operators).

2 - COMPONENTS OF THE SYSTEM

Touch-less switch **manusa** SMART-PROX consists of:

- Touch-less switch



- Wire (10 m) and connectors




3 - TECHNICAL FEATURES

Power supply	From 12 to 24 Vcc
Consumption	30 mA
Output	Manusa bus or Relay (N.O.)
Detection range	Adjustable from 5cm to 35cm approx.
Operating temperature range	From 0 to 50 °C
Dimensions	100 x 75 x 26



5 to 35 cm



4 - PART NUMBERS

ELEMENTS

Touch-less switch Smart-Prox

PART NO.

A02858

NOTE: The features included in this document are given for information purposes only, and are not binding.

The manufacturer reserves the right to modify its products without prior notice.

Last updated: March 2011

HEAD OFFICE
 Av. Vía Augusta, 85-87, 6th
 08174 Sant Cugat del Vallés
 Barcelona - Spain
 Tel. +34 902 321 400
 Fax +34 902 321 450

FACTORY
 Ctra. Pla de Sta. María 235-239
 43800 Valls - Tarragona (Spain)
 Tel. +34 902 321 700
 Fax +34 902 321 750

www.manusa.com